# G3VM-31QR/61QR2/101QR1


MOS FET Relays S-VSON(L) 4Pin, High-current and Low-ON-resistance Type

### Compact S-VSON(L) Package **MOS FET Relays with High Capacity Switching**

- A compact L2.0 × W1.45 × H1.3 mm S-VSON(L) package helps to reduce the space required by circuit boards.
- Weighs just 0.01 g per item, helping to reduce the weight of the circuit boards.
- Load voltage 30 V/60 V/100 V.

30-V Relay: Continuous load current of 1.5 A max. 60-V Relay: Continuous load current of 1.0 A max. 100-V Relay: Continuous load current of 0.65 A max.

• High Ambient operating temperature: -40°C to +110°C





Note: The actual product is marked differently from the image shown here.

### ■Application Examples


- · Semiconductor test equipment
- Test & measurement equipment
- Communication equipment
- Data loggers

### ■Package (Unit:mm, Average)

### ■ Model Number Legend

G3VM-

S-VSON(L) 4Pin



Note: The actual product is marked differently from the image shown here.

1. Load Voltage

3: 30 V 6: 60 V

10: 100 V

4. Additional functions R: Low On-resistance 2. Contact form Package type 1: 1a (SPST-NO)

3. Package type Q: S-VŠON(L) 4Pin

5. Other information

When specifications overlap. serial code is added in the recorded order.

### ■Ordering Information

Package type	Contact form	Terminals	Load voltage (peak value) *	Continuous load current (peak value) *	Packing/Tape cut		Packing/Tape & reel	
					Model	Minimum package quantity	Model	Minimum package quantity
	1a (SPST-NO)	Surface-mounting Terminals	30 V	1,500 mA	G3VM-31QR	1 pc.	G3VM-31QR (TR05)	500 pcs.
S-VSON(L) 4			60 V	1,000 mA	G3VM-61QR2		G3VM-61QR2 (TR05)	
			100 V	650 mA	G3VM-101QR1		G3VM-101QR1 (TR05)	

\* The AC peak and DC value are given for the load voltage and continuous load current.

Note: Taping cut products are packaged without humidity resistance. Use manual soldering to mount them.

### ■Absolute Maximum Ratings (Ta = 25°C)


Item		Symbol	G3VM-31QR	G3VM-61QR2	G3VM-101QR1	Unit	Measurement conditions	
LED forward current		lF		30	mA			
Ħ	其 LED forward current reduction rate		-0.3			mA/°C	Ta≥25°C	
lnp	LED reverse voltage		5			V		
	Connection temperature		125			°C		
	Load voltage (AC peak/DC)		30	60	100	V		
Ħ	Continuous load current (AC peak/DC)	lo	1500	1000	650	mA		
Outpi	ON current reduction rate	Δlo/°C	-15	-10	-6.5	mA/°C	Ta≥25°C	
0	Pulse ON current	lop	4.5	3	2	Α	t=100 ms, Duty=1/10	
	Connection temperature	TJ	125			°C		
Die	Dielectric strength between I/O *		500			Vrms	AC for 1 min	
Ambient operating temperature		Та	-40 to +110			°C	With no icing or condensation	
Ambient storage temperature		Tstg	-40 to +125			°C	With no long of condensation	
Soldering temperature		-	260			°C	10 s	

<sup>\*</sup> The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.

### ■Electrical Characteristics (Ta = 25°C)

	Item	Syn	nbol	G3VM-31QR	G3VM-61QR2	G3VM-101QR1	Unit	Measurement conditions		
		VF	Minimum	1.1			٧			
	LED forward voltage		Typical	1.21				I <sub>F</sub> =10 mA		
			Maximum	1.4						
Input	Reverse current	lr	Maximum		10		μΑ	V <sub>R</sub> =5 V		
트	Capacity between terminals	Ст	Typical	30			pF	V=0, f=1 MHz		
	Trigger LED forward current	lft	Typical	0.6	0.6 0.7			lo=100 mA		
	Trigger LED forward current	IFI	Maximum	3			mA	10-100 IIIA		
	Release LED forward current	IFC	Minimum		0.1		mΑ	Ioff=10 μA		
		Ron	Typical	0.1	0.2	0.4		G3VM-31QR/61QR2,		
	Maximum resistance with output ON		Maximum	0.2	0.3	0.6	Ω	lo=1000 mA, I <sub>F</sub> =5 mA, t<1 s G3VM-101QR1, lo=650 mA, I <sub>F</sub> =5 mA, t<1 s		
Output	Current leakage when the relay is open	Ileak	Maximum	1	1000 (1)				nA	G3VM-31QR :Voff= 20 V G3VM-61QR2 :Voff= 60 V (Voff= 50 V) G3VM-101QR1 :Voff= 100 V (Voff= 80 V)
	Capacity between terminals	Coff	Typical	120	80	50	pF	V=0, f=100 MHz, t<1 s		
	Capacity between terminals		Maximum	ı	150	-	рі	V-0, 1-100 WII 12, t-1 5		
Ca	pacity between I/O terminals	C <sub>I-O</sub>	Typical	1	0.9		pF	f=1 MHz, Vs=0 V		
	ulation resistance between I/O minals	R <sub>I</sub> -o	Typical	108		$M\Omega$	V⊦o=500 VDC, RoH≤60%			
т	rn-ON time	ton	Typical	0.8	0.75 0.6		ms			
Tu	III-ON UIIIE		Maximum	2		1115	I <sub>F</sub> =5 mA, R <sub>L</sub> =200 Ω,			
Tu	rn-OFF time	toff	Typical	0.05	0.05 0.04		ms	V <sub>DD</sub> =20 V *		
Tu	III-OI I WIIIC	LUFF	Maximum	1	0	0.3				

#### Turn-ON and Turn-OFF Times





### ■Recommended Operating Conditions


For usage with high reliability, Recommended Operation Conditions is a measure that takes into account the derating of Absolute Maximum Ratings and Electrical Characteristics.

Each item on this list is an independent condition, so it is not simultaneously satisfy several conditions.


Item	Symbol		G3VM-31QR	G3VM-61QR2	G3VM-101QR1	Unit
Load voltage (AC peak/DC)	Vdd	Maximum	24	48	80	V
		Minimum		5		
Operating LED forward current	lF	Typical		mA		
		Maximum	20			
Continuous load current (AC peak/DC)	lo	Maximum	1300	1000	650	
Ambient operating temperature	Та	Minimum		°C		
Ambient operating temperature	l la	Maximum	100			

### **■**Engineering Data


### LED forward current vs. Ambient temperature




### Continuous load current vs. Ambient temperature




### LED forward current vs. LED forward voltage




### Continuous load current vs. On-state voltage




### On-state resistance vs. Ambient temperature




Trigger LED forward current vs. Ambient temperature




## ●Turn ON, Turn OFF time vs. LED forward current




●Turn ON, Turn OFF time vs. Ambient temperature




Current leakage vs. Load voltage



#### Current leakage vs. Ambient temperature



### Output terminal capacitance vs. Load voltage




### ■Appearance / Terminal Arrangement / Internal Connections

#### **■**Appearance

#### S-VSON (Super-Very Small Outline Non-leaded)


S-VSON(L) 4Pin



\* Actual model name marking for each model

each model					
Model	Marking				
G3VM-31QR	3Q0				
G3VM-61QR2	6Q2				
G3VM-101QR1	AQ1				

# ■Terminal Arrangement/Internal Connections (Top View)



Note 1. The actual product is marked differently from the image shown here.

2. "G3VM" does not appear in the model number on the Relay.

### **■**Dimensions

CAD Data marked products, 2D drawings and 3D CAD models are available. For CAD information, please visit our website, which is noted on the last page


(Unit: mm)

S-VSON(L) 4Pin

#### **Surface-mounting Terminals**

Weight: 0.01 g






Note: The actual product is marked differently from the image shown here.

#### **Actual Mounting Pad Dimensions**

(Recommended Value, Top View)



**Note:** Unless otherwise specified, the dimensional tolerance is ± 0.1 mm.

CAD Data

### **■**Safety Precautions

• Refer to "Common Precautions" for all G3VM models.

Please check each region's Terms & Conditions by region website.

**OMRON Corporation Device & Module Solutions Company** 

#### **Regional Contact**

Americas

https://components.omron.com/us

Asia-Pacific

https://components.omron.com/ap

https://components.omron.com/kr

Europe

https://components.omron.com/eu

China

https://components.omron.com.cn

Japan

https://components.omron.com/jp